

Handheld Digital Multimeter



Features

- Low cost digital multimeter
- Measures DC & AC voltage measurements
- DC current and transistor hFE measurement
- Resistance, diode and test signal measurement
- Audible continuity test
- LCD 3½ digits (1999 count) 0.5" high display
- Automatic, indicated minus, assumed plus polarity
- Measure method: double integral A/D switch implement
- 2 times per second sampling speed
- 9V NEDA 1604 or 6F22 battery powered

Specifications

Max. Display	: LCD 3½ digits (1999 count) 0.5" high
Polarity	: Automatic, indicated minus, assumed plus.
Measure Method	: Double integral A/D switch implement
Sampling Speed	: 2 times per second
Over-Load Indication	: "1" is displayed
Operating Temperature	: 0°C to +40°C, at <80%RH
Storage Temperature	: -10°C to +50°C, at <85%RH
Power	: 9V NEDA 1604 or 6F22
Low Voltage Indication	: "BAT"
Static Electricity	: Approx 4mA
Dimension	: 126mm×70mm×26mm
Weight	: 180g (including battery)

Part Number Table

Description	Part Number
Handheld Digital Multimeter, 1999	D03047

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. DURATOOL is the registered trademark of Premier Farnell Limited 2019.

Newark.com/exclusive-brands
Farnell.com/exclusive-brands
Element14.com/exclusive-brands

